FLX Spot DVS Swivel

LOCATION **TYPE** DATE **PROJECT**





PRODUCT FEATURES

- Ultra Slim Profile
- Single Diode Provides Single Crisp Image
- Linkable Units (Link up to 7 units together)
- Recessed Mount or Surface Mount
- Control with 0-10V, DALI, DMX, Zigbee
- Quick Ship Available

■ PRODUCT SPECIFICATIONS

Power Input	24V DC Constant Voltage				
Color Rendering Index	CRI>90				
Available CCTs	2700K, 3000K, 3500K, 4000K, 5700K				
Energy Efficiency	100lm/W				
Operating Tempaerature Ranges	0-45°C (32-113°F)				
Control	0-10V, DALI, DMX, Zigbee				
Finish	Black, White, Silver (Special Order Option- Bronze)				
Beam Angle	60° (STD), 25° and 45° (Special Order Option)				
Lamp Life	50,000hr / 70%				
Warranty	5 year				
Note	Product is approved for Closet / Storage space installation per NEC410.16 (A) (3) and NEC410.16 (C)(5) per NRTL certifiaction				

SPECIFICATION










Performance data shown below for 4000K CCT. Refer to individual luminaire IES files for other CCT options.									
	Model Name	Power Input	Lamp Power	Luminous Flux	Luminous Efficacy	Color Rendering Index	Color Temperature	Beam Angle	Operating Temperature
	DVS4A (color)K-24V-SW-25	DC 24V	4.5 W	487 lm	108 lm/w	CRI > 90	2700K, 3000K, 3500K, 4000K	25° *	0-45°C (32-113°F)
	DVS4A (color)K-24V-SW-45		4.6 W	502 lm	109 lm/w	CRI > 90		45° *	
	DVS4A (color)K-24V-SW-60		4.6 W	485 lm	105 lm/w	CRI > 90		60°	

^{* 25} or 45 degree are special options


SPECIFICATION GUIDE



FLX Spot DVS Swivel

DIMENSION

*Recessed Mount



INSTALLATION

Linkable between FLX Spot DVS Swivel & FLX Spot DVS Swivel






Linkable between NDP & FLX Spot DVS Swivel





★ Linkabel between FLX Spot DVS and FLX Spot DVS (Max. 7 units connectable in a row/LED Driver)

···· C90 / C270



Admissible distances for blind hole installation in boards with a thickness of at least 19mm(0.75")






When depth for blind hole is 16mm(0.63")

When depth for blind hole is more than 25mm(0.98")







BEAM SPREADS

- CO / C180

DVS4A 40K-24V-SW-25

cd / 1000lm







FLX Spot DVS Swivel

COMPONENTS



FLX Spot DVS Swivel

- __DVS4A (color)K-24V-SW-BK __DVS4A (color)K-24V-SW-WT __DVS4A (color)K-24V-SW-SV
- Other finishes available as special order



Dimming Interface (0-10V)

__FDC-L10 * Max. 100W (100W/CH, 1CH)



12 Port Hub

__D12P-HUB Included with Cord and Plug drivers. Order separately for Hard Wire or 3rd Party Drivers



Extension cable

__DVSPTC (2,500mm/98.43")



Control Interface (0-10V)

__FDD-L20 Max. 200W (100W/CH, 2CH)



LED Drivers

__ FLC30-24V/XL (30W) * __ FLC75-24V/XL (75W) * With distributor and power cord 1800mm (6')



Connecting cable

__NDPDVSPTC (1,000mm/39.37")

• For Linking Linear Fixtures



Control Interface (DALI)

__FDD-L1DA Max. 200W (100W/CH, 1CH)



Driver Junction Box

__ MHWB-FLE



Connecting cable

__NDVPC (2,500mm/98.43")

For Linking Linear Fixtures



Control Interface (0-10V,DMX512)

__FDA-L2MO Max. 200W (100W/CH, 2CH) __FDA-L5M Max. 200W (50W/CH, 5CH)



Hard Wire Driver

__XLD200-224V-FCL-DIM (0-10V) __XLD75-124V-FC* (90V to 300V)



Connecting cable

__NDPPC (2,500mm/98.43")

• For Linking Linear Fixtures



Control Interface (Zigbee)

FDD-L2Z



Hard Wire Driver

__FLE60-24V-L10-DIM (Linear) __FLE90-24V-L10-DIM (Linear)



Wireless Control (Zigbee Switch)

__FSM-Z1

A larger selection of drivers are available including remote and hard wire drivers. Please consult factory.

* FLC30, FLC75 and XLD75 require the FDC-L10 for 0-10V dimming



Door and motion sensor

__FLS-M24V



Occupancy sensor

__FLS-P24V